

# ALZM04B



## Product

Presentation Timer w/ Large LED Display

### Description:

This presentation TimeKeeper™ system includes a TMR221B8 Count Up/Down Timer with three programmable presets, RYG11ABBK and a DSP254B Large Four-digit LED wall Display visible (up to 50ft) to the speaker and the audience.

**Item:** ALZM04B

**UPC:** 788581650202

**EAN:** 0788581650202

**Stock Status:** Usually in stock.

**Dimensions:** 11.0" x 4.5" x 2.5"

**Weight:** 5.1 lbs.

**MSRP:** \$999.00

### Specifications:

- Two Serial data RJ11 connectors for accessories.
- One RS422 output with RJ45 connector for accessories.
- Ground closure 600mA output for optional beeper. (not included).
- Timer Construction: Metal enclosure, black powder coated finish.
- Display Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 350ma.
- TMR221B8\_SM Dimensions: 4.5" x 4.5" x 1.25".

- DSP254B Dimensions: 11" x 4.5" x 2".
- RYG11ABBK Dimensions: 5.63" x 3.25" x 1.5".

### Features:

- Count up elapsed timer settable to Hour:Min or Min:Sec.
- Count down time remaining timer settable to Hour:Min or Min:Sec.
- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Green, Yellow and Red warning indicators have preprogrammed settings to match Toastmasters requirements, or may be programmed by user.
- Four-digit LED seven-segment Display with 0.56 inch high digits.
- Beeper provides audible sound when timer reaches zero.
- Button to turn beeper on/off.
- Built in Time of day clock displays 12 or 24 hour mode.
- Connect two or more TimeKeepers™ together. One becomes the Timer, and the others become remote Displays.
- Made of ruggedized aluminum construction.
- Convenience is important to most people. This gives you an advantage as Alzatex timers are easy to use. The real benefit to you is a very quick learning curve.

### Item Includes:

- (1) TMR221B8-SM Count up/down timer.
- (1) DSP254B Large LED Display.
- (1) RYG11ABBK Green-Yellow-Red Indicator lamp module.
- (1) WT12VAC1200MA-RA 12V AC, 1200 MA Transformer.
- (1) M4C007F 7ft standard 4-conductor phone cord.
- (1) M4X007F 7ft crossover 4-conductor phone cord.
- (1) RC Reference card.
- (1) WD Wiring diagram.

### Optional Accessories:

- (1) DSP1016B0 Quad 4-Digit LED display with 1 inch high digits.
- (1) DSP254B 4-Digit LED display with 2-1/3 inch high digits.
- (1) DSP256B 4-Digit LED display with 2-1/3 inch high digits.
- (1) DSP418B LED display with four 4-inch high digits, four 1-inch high digits and RYG lamps.
- (1) DSP504B 4-Digit LED display with 5 inch high digits.
- (1) DSP506B 6-Digit LED display with 5 inch high digits.
- (1) DSP704B 4-Digit LED display with 7 inch high digits.

| sales@alzatex.com | S00X

- (1) DSP706B 6-Digit LED display with 7 inch high digits.
- (1) DSP1004B 4-Digit LED display with 10 inch high digits.
- (1) DSP1006B 6-Digit LED display with 10 inch high digits.
- (1) RYG11ABBK Red-Yellow-Green Indicator Lamps with 1/2 inch domes.
- (1) RYG200A Red-Yellow-Green Indicator lamps with 2 inch LED clusters.
- (1) RYG472AB Red-Yellow-Green Indicator Lamps with 4 inch LED clusters.
- (1) PS60W150 15VDC, 4A Power Supply with 6ft power cord.
- (1) ADD-BEEP Loud Beeper.