

ALZM07B



Product

Presentation Timer w/ Large LED Display

Description:

This wireless presentation TimeKeeper™ system includes a TMR216B_RF2 Count Up/Down Timer with multiple programmable presets, and a DSP504B Large Four-digit LED wall Display visible (up to 100ft) to the speaker and the audience.

Item: ALZM07B

UPC: 788581654668

EAN: 0788581654668

Stock Status: Usually in stock.

Dimensions: 21.5" x 8.0" x 2.5"

Weight: 9.2 lbs.

MSRP: \$1,299.00

Specifications:

- Two Serial data RJ45 connectors for accessories.
- One RS422 output with RJ45 connector for accessories.
- Ground closure 600mA output for optional beeper. (not included).
- Timer Construction: Metal enclosure, black powder coated finish.
- Display Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 500ma.
- TMR216B_RF2 Dimensions: 9.5" x 4.625" x 2.5".
- DSP504B Dimensions: 21.5" x 8" x 2.5".

- Standard mounting is 2 key hole slots spaced 16 inches apart for wall mounting.
- There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- 1/4-20 nuts on the bottom of the unit for attaching a tripod adapter or feet. The feet and tripod adapter is NOT included and may be ordered separately.
- The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

Features:

- Keypad has 18 buttons and a knob.
- Programmable buttons to perform a variety of functions.
- Factory programmed to fit your application.
- Serial data output to send commands to a remote Display, Timer or other device.
- Serial data input to permit daisy chaining multiple keypads/controllers.
- Battery operation or AC power.
- Count up elapsed timer settable to Hour:Min or Min:Sec.
- Count down time remaining timer settable to Hour:Min or Min:Sec.
- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Green, Yellow and Red warning indicators have preprogrammed settings to match Toastmasters requirements, or may be programmed by user.
- Six-digit LED fourteen-segment alpha-numeric Display with 0.54 inch high digits
- Beeper provides audible sound when timer reaches zero.
- Button to turn beeper on/off.
- Connect two or more TimeKeepers™ together. One becomes the Timer, and the others become remote Displays.
- Made of ruggedized aluminum construction.
- Convenience is important to most people. This gives you an advantage as Alzatex timers are easy to use. The real benefit to you is a very quick learning curve.

Item Includes:

- (1) TMR216B6-RF2 Wireless keypad with 18 buttons and a knob.
- (1) DSP504B Large LED Display.
- (1) ADD-RF-MX04A RF 2.4GHZ Transceiver, for top of Display.
- (2) WT12VAC1200MA-RA 12V AC, 1200mA Transformer.
- (1) RC Reference card.
- (1) WD Wiring diagram.

Optional Accessories:

- (1) RYG11ABBK Red-Yellow-Green Indicator Lamps.
- (1) RYG472AB Red-Yellow-Green Indicator Lamps.
- (1) DSP1016B0 Quad 4-Digit LED display with 1 inch high digits.
- (1) DSP254B 4-Digit LED display with 2-1/3 inch high digits.
- (1) DSP256B 4-Digit LED display with 2-1/3 inch high digits.
- (1) DSP418B LED display with four 4-inch high digits, four 1-inch high digits and RYG lamps.
- (1) DSP504B 4-Digit LED display with 5 inch high digits.
- (1) DSP506B 6-Digit LED display with 5 inch high digits.
- (1) DSP704B 4-Digit LED display with 7 inch high digits.
- (1) DSP706B 6-Digit LED display with 7 inch high digits.
- (1) DSP1004B 4-Digit LED display with 10 inch high digits.
- (1) DSP1006B 6-Digit LED display with 10 inch high digits.
- (1) RYG11ABBK Red-Yellow-Green Indicator Lamps with 1/2 inch domes.
- (1) RYG200A Red-Yellow-Green Indicator lamps with 2 inch LED clusters.
- (1) RYG472AB Red-Yellow-Green Indicator Lamps with 4 inch LED clusters.
- (1) PS60W150 15VDC, 4A Power Supply with 6ft power cord.
- (1) ADD-BEEP Loud Beeper.