

ALZW28A



Product

Take-A-Number PRO system, sd card

Description:

This waiting line management package includes a hard-wired buttons and Take-a-number PRO controller with SD Card Memory for capturing wait times, number of people waiting and a host of other events and a 4.2" alphanumeric display. This system may also be expanded to serve up to six different services at multiple windows. One indicator is placed over each respective window.

Item: ALZW28A

UPC: 788581657409

EAN: 0788581657409

Dimensions: 52.0" x 16.0" x 16.0"

Weight: 42.98 lbs.

MSRP: \$4,878.50

Specifications:

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Two RJ11 modular connectors for accessories.
- RJ11 modular connector for remote button inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 100mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.
- DC117B6_WAIT1 Dimensions: 6.4" x 3.7" x 2.5".

Features:

- Convenience is important to most people. This gives you an advantage as Alzatex timers are easy to use. The real benefit to you is a very quick learning curve.
- 7x40 Pixel 4.2" alphanumeric LED display showing Now Serving ticket number and Window number.
- Standard mounting is 2 key hole slots spaced 9 inches apart for wall mounting.
- There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- There is one 1/4-20 nut on the bottom of the unit for attaching camera style tripod.
- Includes Take-A-Turn ticket printer with one request service (ticket print) button.
- Two push buttons can be installed for multiple windows.

Item Includes:

- (2) DSA478B-OAK-NSW Large LED Display.
- (2) PB1-WH White Push Button.
- (2) NL16AG Indicator Lamp.
- (1) RLY15A-GC Ground Closure Module.
- (1) PR121C2 TAT Ticket Printer.
- (1) PR921A1R Thermal Printer Paper (1 Roll).
- (1) DC117B6-WAIT1 TAT Printer Controller.
- (1) KTP7X422A-8B Button Input Module.
- (1) M2C22G050F 50ft, 22ga, 2-conductor wire.
- (3) M8BK050F 50ft, Cat-5, 8-conductor cable.
- (2) M8BK003F 3ft, Cat-5, 8-conductor Cable.
- (1) PSYM04-120 Power Supply, 12VDC, 9A.
- (1) RC Reference card.
- (1) WD Wiring diagram.